PANDORA
Lights

Desk
1x High End Roadhog 4 (software Version 3.19.0(B3460)
1x Roadhog 3 Playback Wing

Dimmers
48x ETC SensorRack 2,3KW
12x DimmerChannel 2,3KW StageRight Floor

Stage roof - Conventional
8x Showtec Cateye Blinder 500W
3x ACL Aircraft Set

Stage roof - Intelligent
8x Martin Quantum Profile
8x Martin Mac Aura XB
6x Martin Atomic 3000 strobe
12x Colordash Par H7
4x CLF Hercules (side lights)

Stage floor - Intelligent
4x Martin Quantum Profile
4x Martin Mac Aura XB

Stage floor – Conventional
6x Par64 Floorcan

Frontlight (fixed in LX3 & LX4)
8x Robert Juliat Profile 614SX
4x Chauvet Ovation F-265WW

Houselights (all fixed)
4x Martin Quantum Profile
6x Martin Mac Aura XB
23x Colordash Par H7

Haze/fog
1x MDG ATME + ADJ DMX Fan
1x Look Solutions Viper 2.6

On - stage Power
Stage Left:
1x CEE32A 3ph+N+PE
1x CEE16A 1ph+N+PE

Stage Right:
1x CEE125A 3ph+N+PE
1x CEE32A 3ph+N+PE
1x CEE16A 1ph+N+PE

sACN
All lights are controlled by sACN

Housedesk starts on sACN 1 Priority 100
Guestdesk starts on sACN 1 Priority 200

DMX-Patch Line 1: Conventional – Led
DMX-Patch Line 2: Spots
DMX-Patch Line 3: Wash
DMX-Patch Line 4: Free
DMX-Patch Line 5: Free
DMX-Patch Line 6: Free
DMX-Patch Line 7: Free
DMX-Patch Line 8: Free
DMX-Patch Line 9: Free
DMX-Patch Line 10: Free
DMX-Patch Line 11: Free
DMX-Patch Line 12: Free

Lightplot
Separated

Download Information

LightPlot
Capture File
Vectorworks

PANDORA
PatchList

sACN 1 - DMX Line 1 Conventional - LED Housedesk Priority 100	Count on universe: 19x Dimmer Channels 12x Dimmer Floor Channels 4xChauvet Ovation F-265WW 2CH Mode 35x LedPar (8CH Mode)

#	Description	Where	Address	Remark
101	CatEye	LX1	1	
102	CatEye	LX1	2	
103	CatEye	LX1	3	
104	CatEye	LX1	4	
105	ACL	LX1 Outside	5	
106	ACL	LX1 Inside	6	
113	CatEye	LX2	13	
114	CatEye	LX2	14	
115	CatEye	LX2	15	
116	CatEye	LX2	16	
117	ACL	LX2	17	
119	Robert Juliat Profile 614SX	LX3	19	
120	Robert Juliat Profile 614SX	LX3	20	
121	Robert Juliat Profile 614SX	LX3	21	
125	Robert Juliat Profile 614SX	LX4	25	
126	Robert Juliat Profile 614SX	LX4	26	
127	Robert Juliat Profile 614SX	LX4	27	
128	Robert Juliat Profile 614SX	LX4	28	
129	Robert Juliat Profile 614SX	LX4	29	
131	Chauvet Ovation F-265WW	LX4	61	2 Channel
132	Chauvet Ovation F-265WW	LX4	63	2 Channel
133	Chauvet Ovation F-265WW	LX4	65	2 Channel
134	Chauvet Ovation F-265WW	LX4	67	2 Channel
149	DimmerChannel	StageRight Floor	49	
150	DimmerChannel	StageRight Floor	50	
151	DimmerChannel	StageRight Floor	51	
152	DimmerChannel	StageRight Floor	52	
153	DimmerChannel	StageRight Floor	53	
154	DimmerChannel	StageRight Floor	54	
155	DimmerChannel	StageRight Floor	55	
156	DimmerChannel	StageRight Floor	56	
157	DimmerChannel	StageRight Floor	57	
158	DimmerChannel	StageRight Floor	58	
159	DimmerChannel	StageRight Floor	59	
160	DimmerChannel	StageRight Floor	60	
	Free DMX Channels		30 t/m 48	
	Free DMX Channels		69 t/m 100	

51	Colordash Par H7	LX1	101	8 Channels
52	Colordash Par H7	LX1	109	8 Channels
53	Colordash Par H7	LX1	117	8 Channels
54	Colordash Par H7	LX1	125	8 Channels
55	Colordash Par H7	LX1	133	8 Channels
56	Colordash Par H7	LX1	141	8 Channels
57	Colordash Par H7	LX2	149	8 Channels
58	Colordash Par H7	LX2	157	8 Channels
59	Colordash Par H7	LX2	165	8 Channels
60	Colordash Par H7	LX2	173	8 Channels
61	Colordash Par H7	LX2	181	8 Channels
62	Colordash Par H7	LX2	189	8 Channels
63	Colordash Par H7	LX3	197	8 Channels
64	Colordash Par H7	LX3	205	8 Channels
65	Colordash Par H7	LX3	213	8 Channels
66	Colordash Par H7	LX3	221	8 Channels
67	Colordash Par H7	LX3	229	8 Channels
68	Colordash Par H7	LX3	237	8 Channels
69	Colordash Par H7	LX4	245	8 Channels
70	Colordash Par H7	LX4	253	8 Channels
71	Colordash Par H7	LX4	261	8 Channels
72	Colordash Par H7	LX4	269	8 Channels
73	Colordash Par H7	LX4	277	8 Channels
74	Colordash Par H7	LX4	285	8 Channels
75	Colordash Par H7	LX5	293	8 Channels
76	Colordash Par H7	LX5	301	8 Channels
77	Colordash Par H7	LX5	309	8 Channels
78	Colordash Par H7	LX5	317	8 Channels
79	Colordash Par H7	LX5	325	8 Channels
80	Colordash Par H7	LX5	333	8 Channels
81	Colordash Par H7	LX6	341	8 Channels
82	Colordash Par H7	LX6	349	8 Channels
83	Colordash Par H7	LX6	357	8 Channels
84	Colordash Par H7	LX6	365	8 Channels
85	Colordash Par H7	LX6	373	8 Channels
86	Colordash Par H7	LX6	381	8 Channels
87	Colordash Par H7	Balcony Left	389	8 Channels
88	Colordash Par H7	Balcony Left	397	8 Channels
89	Colordash Par H7	Balcony Back	405	8 Channels
90	Colordash Par H7	Balcony Back	413	8 Channels
91	Colordash Par H7	Balcony Back	421	8 Channels
92	Colordash Par H7	Balcony Back	429	8 Channels
93	Colordash Par H7	Side Stage	437	8 Channels
94	Colordash Par H7	Side Stage	445	8 Channels
95	Colordash Par H7	Side Stage	453	8 Channels
96	Colordash Par H7	Side Stage	461	8 Channels
97	Colordash Par H7	Side Stage	469	8 Channels
	Free DMX Channels		477 t/m 512	

sACN 2 - DMX Line 2 Spot + Strobe Housedesk Priority 100	Count on universe: 12x Quantum Profile (Basic Mode) 6x Atomic 3000 (4 Channel Mode) 4x CLF Hercules (8 Channel Mode)

#	Description	Where	Address	Remark
1	Martin Quantum Profile	LX1	1	Basic Mode
2	Martin Quantum Profile	LX1	20	Basic Mode
3	Martin Quantum Profile	LX1	39	Basic Mode
4	Martin Quantum Profile	LX1	58	Basic Mode
5	Martin Quantum Profile	LX2	77	Basic Mode
6	Martin Quantum Profile	LX2	96	Basic Mode
7	Martin Quantum Profile	LX2	115	Basic Mode
8	Martin Quantum Profile	LX2	134	Basic Mode
9	Martin Quantum Profile	LX3	153	Basic Mode
10	Martin Quantum Profile	LX3	172	Basic Mode
11	Martin Quantum Profile	LX4	191	Basic Mode
12	Martin Quantum Profile	LX4	210	Basic Mode
13	Martin Quantum Profile	Stage Floor	229	Basic Mode
14	Martin Quantum Profile	Stage Floor	248	Basic Mode
15	Martin Quantum Profile	Stage Floor	267	Basic Mode
16	Martin Quantum Profile	Stage Floor	286	Basic Mode
47	CLF Hercules	Side DSR	305	8 Channels
48	CLF Hercules	Side USR	313	8 Channels
49	CLF Hercules	Side USL	321	8 Channels
50	CLF Hercules	Side DSL	329	8 Channels
	Free DMX Channels		337 t/m 468	
41	Martin Atomic 3000 DMX	LX1	469	4 Channel Mode
42	Martin Atomic 3000 DMX	LX1	473	4 Channel Mode
43	Martin Atomic 3000 DMX	LX2	477	4 Channel Mode
44	Martin Atomic 3000 DMX	LX2	481	4 Channel Mode
45	Martin Atomic 3000 DMX	LX3	485	4 Channel Mode
46	Martin Atomic 3000 DMX	LX3	489	4 Channel Mode
	Free DMX Channels		493 t/m 506	
1001	MDG ATME		507	3 Channels
1002	ADJ Entour Cyclone		510	1 Channel
1003	Look Solutions Viper 2.6		511	1 Channel

sACN 3 - DMX Line 3
Wash
Housedesk Priority 100

Count on universe:
18x Aura XB (Extended Mode)

#	Description	Where	Address	Remark
21	Martin Mac Aura XB	LX1	1	Extended Mode
22	Martin Mac Aura XB	LX1	26	Extended Mode
23	Martin Mac Aura XB	LX1	51	Extended Mode
24	Martin Mac Aura XB	LX1	76	Extended Mode
25	Martin Mac Aura XB	LX2	101	Extended Mode
26	Martin Mac Aura XB	LX2	126	Extended Mode
27	Martin Mac Aura XB	LX2	151	Extended Mode
28	Martin Mac Aura XB	LX2	176	Extended Mode
29	Martin Mac Aura XB	LX4	201	Extended Mode
30	Martin Mac Aura XB	LX4	226	Extended Mode
31	Martin Mac Aura XB	LX5	251	Extended Mode
32	Martin Mac Aura XB	LX5	276	Extended Mode
33	Martin Mac Aura XB	LX5	301	Extended Mode
34	Martin Mac Aura XB	LX5	326	Extended Mode
35	Martin Mac Aura XB	Stage Floor	351	Extended Mode
36	Martin Mac Aura XB	Stage Floor	376	Extended Mode
37	Martin Mac Aura XB	Stage Floor	401	Extended Mode
38	Martin Mac Aura XB	Stage Floor	426	Extended Mode
	Free DMX Channels		451 t/m 512	

sACN 4 t/m 12 - DMX Line 4 t/m 12
Free Line
Housedesk Priority 100

#	Description	Where	Address	Remark
4 t/m 12	Free			Free Universe To Use

IP-Adresses Light Network Pandora

House Desk	Fixture Net	
Roadhog 4	10.98.176.201	
LuminexNode12	10.98.176.211	