

HERTZ

Lights

Desk

1x High End Roadhog 4 (software Version 3.19.0 b3460)
1x Roadhog 3 Playback Wing

Dimmers

6x Free dimmer Channels in LX1
6x Free dimmer Channels on stage center

Stage roof - Conventional

24x ETC S4 Par Narrow
(fixed Focus & Position)

Stage roof - Intelligent

6x Martin Era 300 Profile
6x Martin Mac Aura XB
6x Colordash Par H7

Stage - Intelligent

8x Prolights LumiPix 12QTour

FrontLight - Conventional (fixed)

14x Robert Juliat Profile 614SX
6x Robert Juliat PC 329HPC
2x ADB DW105 Profile

Haze/fog

1x MDG Atmosphere

sACN

All lights are controlled by sACN

Housedesk starts on sACN 1 Priority 100
Guestdesk starts on sACN 1 Priority 200

DMX-Patch Line 1: Conventional - Led
DMX-Patch Line 2: Spots - Wash - Led
DMX-Patch Line 3: Free
DMX-Patch Line 4: Free

Lightplot
Separated

Download Information

[LightPlot](#)
[Capture File](#)
[Vectorworks](#)

HERTZ

PatchList

sACN 1 - DMX Line 1
Conventional
Housedesk Priority 100

Count on universe:
20x Dimmer Channels (Front Light)
22x Dimmer Channels (Orchestra Light)
4x Dimmer Channels (Side Light)
6x Free Dimmer Channels (Stage Center)
6x Free Dimmer Channels (LX1)

#	Description	Where	Address	Remark
101	Robert Juliat Profile 614SX	Front	1	
102	Robert Juliat Profile 614SX	Front	2	
103	Robert Juliat Profile 614SX	Front	3	
104	Robert Juliat PC 329HPC	Front	4	
105	Robert Juliat Profile 614SX	Front	5	
106	Robert Juliat PC 329HPC	Front	6	
107	Robert Juliat Profile 614SX	Front	7	
108	Robert Juliat Profile 614SX	Front	8	
109	Robert Juliat PC 329HPC	Front	9	
110	Robert Juliat Profile 614SX	Front	10	
111	Robert Juliat Profile 614SX	Front	11	
112	Robert Juliat PC 329HPC	Front	12	
113	Robert Juliat Profile 614SX	Front	13	
114	Robert Juliat Profile 614SX	Front	14	
115	Robert Juliat PC 329HPC	Front	15	
116	Robert Juliat Profile 614SX	Front	16	
117	Robert Juliat PC 329HPC	Front	17	
118	Robert Juliat Profile 614SX	Front	18	
119	Robert Juliat Profile 614SX	Front	19	
120	Robert Juliat Profile 614SX	Front	20	
121	ADB DW105 Profile	Side Light	29	Gobo Wand
122	ADB DW105 Profile	Side Light	39	Gobo Wand
125	Free Dimmer Channel	LX3	61	
126	Free Dimmer Channel	LX3	62	
127	Free Dimmer Channel	LX3	63	
128	Free Dimmer Channel	LX3	64	
129	Free Dimmer Channel	LX3	65	
130	Free Dimmer Channel	LX3	66	
140	ETC Source4 15-30deg	Front	76	SUTU Gobo
141	Free Dimmer Channel	Stage Center	85	
142	Free Dimmer Channel	Stage Center	86	
143	Free Dimmer Channel	Stage Center	87	
144	Free Dimmer Channel	Stage Center	88	
145	Free Dimmer Channel	Stage Center	89	
146	Free Dimmer Channel	Stage Center	90	
201	ETC S4 Par Narrow	Grid	201	Orchestra Light
202	ETC S4 Par Narrow	Grid	202	Orchestra Light
203	ETC S4 Par Narrow	Grid	203	Orchestra Light

204	ETC S4 Par Narrow	Grid	204	Orchestra Light
205	ETC S4 Par Narrow	Grid	205	Orchestra Light
206	ETC S4 Par Narrow	Grid	206	Orchestra Light
207	ETC S4 Par Narrow	Grid	207	Orchestra Light
208	ETC S4 Par Narrow	Grid	208	Orchestra Light
209	ETC S4 Par Narrow	Grid	209	Orchestra Light
210	ETC S4 Par Narrow	Grid	210	Orchestra Light
211	ETC S4 Par Narrow	Grid	211	Orchestra Light
212	ETC S4 Par Narrow	Grid	212	Orchestra Light
213	ETC S4 Par Narrow	Grid	213	Orchestra Light
214	ETC S4 Par Narrow	Grid	214	Orchestra Light
215	ETC S4 Par Narrow	Grid	215	Orchestra Light
216	ETC S4 Par Narrow	Grid	216	Orchestra Light
217	ETC S4 Par Narrow	Grid	217	Orchestra Light
218	ETC S4 Par Narrow	Grid	218	Orchestra Light
219	ETC S4 Par Narrow	Grid	219	Orchestra Light
220	ETC S4 Par Narrow	Grid	220	Orchestra Light
221	ETC S4 Par Narrow	Grid	221	Orchestra Light
222	ETC S4 Par Narrow	Grid	222	Orchestra Light
	Free DMX Channels		227 t/m 500	
1001	House Light		501	90 —> 255 - 100%
				65 —> 89 - Meelees
				39 —> 63 - Inloop
				0 —> 38 Concert
				No Fade Time Between Cue'
1002	Stairs		508	5-45% Walk in - 55-95% Concert Fadetime 5s
1003	Ceiling		509	
1004	Under Balcony 0		510	
1005	Under Balcony 1		511	
1006	Under Balcony 2		512	
	Free DMX Channels		502 t/m 507	

sACN 2- DMX Line 2
Spot + Wash + Led Stage
Housedesk Priority 100

Count on universe:
6x Era 300
6x Aura XB (Extended Mode)
6x LedPar (8 Channel Mode)
1x JEM Compact Hazer Pro

#	Description	Where	Address	Remark
1	Martin Era 300 Profile	LX3	1	
2	Martin Era 300 Profile	LX3	22	
3	Martin Era 300 Profile	LX3	43	
4	Martin Era 300 Profile	LX3	64	
5	Martin Era 300 Profile	LX3	85	
6	Martin Era 300 Profile	LX3	106	
	Free DMX Channels		127 t/m 200	
11	Martin Mac Aura XB	LX3	201	Extended Mode
12	Martin Mac Aura XB	LX3	226	Extended Mode
13	Martin Mac Aura XB	LX3	251	Extended Mode
14	Martin Mac Aura XB	LX3	276	Extended Mode
15	Martin Mac Aura XB	LX3	301	Extended Mode
16	Martin Mac Aura XB	LX3	326	Extended Mode
	Free DMX Channels		351 t/m 400	
21	Colordash Par H7	LX3	401	8 Channels
22	Colordash Par H7	LX3	409	8 Channels
23	Colordash Par H7	LX3	417	8 Channels
24	Colordash Par H7	LX3	425	8 Channels
25	Colordash Par H7	LX3	433	8 Channels
26	Colordash Par H7	LX3	441	8 Channels
	Free DMX Channels		449 t/m 507	
41	MDG Atmoshere	Stage Floor	508	3 Channels
	Free DMX Channels		511 t/m 512	

sACN 3 - DMX Line 3
Led Line
Housedesk Priority 100

#	Description	Where	Address	Remark
31	Prolights LumiPix 12QTour	Stage	1	49 Channels
32	Prolights LumiPix 12QTour	Stage	50	49 Channels
33	Prolights LumiPix 12QTour	Stage	99	49 Channels
34	Prolights LumiPix 12QTour	Stage	148	49 Channels
35	Prolights LumiPix 12QTour	Stage	197	49 Channels
36	Prolights LumiPix 12QTour	Stage	246	49 Channels
37	Prolights LumiPix 12QTour	Stage	295	49 Channels
38	Prolights LumiPix 12QTour	Stage	344	49 Channels
	Free DMX Channels		393 t/m 512	

sACN 4 - DMX Line 4
Free Line
Housedesk Priority 100

#	Description	Where	Address	Remark
	Free			Free Universe To Use

IP-Adresses Light Network Hertz

House Desk	IP Adres	
Roadhog 4	10.98.180.201	
LuminexNode4	10.98.180.211	